


PHN 17,835



RECEIVED #15

MAR 12 2004 B.D.

Technology Center 2600 3/18/04

## MULTI-CHANNEL AUDIO SIGNAL PROCESSING DEVICE

### BACKGROUND OF THE INVENTION

#### Field Of The Invention

[0001] The invention relates to a multi-channel audio signal processing device ~~provided including with~~ signal supply means for  
5 supplying coded audio signals through several input channels, and  
for each input channel, through separate sub-channels which cover  
distinct frequency sub-band domains, and ~~provided with~~ including one  
or several synthesis or reconstruction filters (SFB) for decoding  
and synthesizing audio signals over the total frequency domain  
10 covered by the sub-band domains.

#### Description Of The Related Art

[0002] It is usual, in this case, to include filter means, such  
as main-related filters or ~~sound~~ sound-widening filter means of a  
15 different kind, downstream of the synthesis or reconstruction  
filters in the signal transport direction, i.e., after the  
reconstruction of the broadband audio signals. The same number of  
synthesis or reconstruction filters will then be present as there  
are input channels. The main-related filters or ~~sound~~ sound-  
20 widening filter means of a different kind, also referred to as  
"incredible sound filters (ISF)", are then constructed as broadband  
filters ~~then~~. Instead of such "incredible sound filters",  
alternative filter means may be provided in the audio signal

processing device, such as, for example, equalization or different tone control filters, ~~to~~. These, too, will be provided downstream of the synthesis or reconstruction filters.

5

SUMMARY OF THE INVENTION

[0003] The invention has for its object to simplify such an audio signal processing device without detracting from the quality of the sound reproduction.

[0004] According to the invention, the multi-channel audio  
10 signal processing device as defined in the opening paragraph is characterized in that (the device further comprises) sub-band combination circuits ~~are present~~, each sub-band combination circuit being supplied with audio signals through respective input channels which lie in one and the same sub-band frequency domain, while the  
15 output signals of a sub-band combination circuit covering an associated frequency sub-domain are supplied to a synthesis filter. This means that only one synthesis or reconstruction filter is necessary for each sound reproduction channel, independently of the number of input channels. For example, if audio signals are offered  
20 to seven input channels, whereas the sound is reproduced through no more than two sound reproduction channels—, e.g., as a result of virtual spatial widening—, only two synthesis or reconstruction filters are necessary, instead of seven as required in the known audio signal processing devices. In a usual stereo sound  
25 reproduction, for example, only 2 or 2.1 synthesis or

reconstruction filters are necessary for 5.1 MPEG input channels. It is usual, in audio signal processing devices, as noted above, to include filter means, such as main-related filters or ~~sound~~-sound-widening filter means of a different type, downstream of the synthesis or reconstruction filters as seen in the signal transport direction. It is also possible to provide, for example, equalization filters in this manner.

[0005] According to the invention, however, it becomes possible to provide filtering means upstream of the synthesis filters as seen in the transport direction. These filter means may then be of a narrow-band type and may, accordingly, be of a simpler construction.

[0006] It is thus possible for the filter means to be included in the connection between associated sub-band combination circuits and a synthesis filter. An equal filtering then takes place for all audio signals supplied through the input sub-channels covering the same frequency sub-domain, which results in an equal filtering of the audio signals supplied through the respective input channels. The filter means may comprise, for example, equalization or different tone control filters in a filtering mode as described above.

[0007] It is also possible for the filter means to be included in the input sub-channels. The filter means may then be of a particularly simple construction, ~~i.~~ It then becomes possible, in particular, to form the filter means by elements which introduce a

scale factor. Irrespective of the location where the filter means  
are is positioned, the filter means may, in either case, comprise  
narrow-band filters for obtaining a desired virtual spatial  
widening from which the audio signals can be heard through distinct  
5 reproduction channels.

#### BRIEF DESCRIPTION OF THE DRAWINGS

[0008] The invention will now be explained in more detail with  
reference to the accompanying drawings, in which:

10 [0009] Fig. 1 shows an audio signal processing device according  
to the present state of the art;

[0010] Fig. 2 shows a first embodiment of an audio signal  
processing device according to the invention, shown for only one  
sound reproduction channel;

15 [0011] Fig. 3 shows a second embodiment of an audio signal  
processing device according to the invention, shown for only one  
sound reproduction channel; and

[0012] Fig. 4 shows a third embodiment of an audio signal  
processing device according to the invention for 2.1 input  
20 channels, only one sound reproduction channel being depicted.

#### DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0013] In the multi-channel audio signal processing device shown  
in Fig. 1, the input signals are derived from a frequency sub-band  
25 encoded storage medium, such as, for example, an optical disc or a

DCC (digital compact cassette), or from a transmission system. The audio signals laid down on this medium or transmitted are distributed over separate channels, and are distributed within each channel over separate frequency sub-bands in accordance with known encoding techniques by means of analysis filter banks. See, for example, "Ken C. Pohlmann, Principals of Digital Audio, 3<sup>rd</sup> ed., McGraw-Hill Inc., 1995", on this subject. The coded signals, obtained from the storage medium or through transmission, are supplied through channels CH1, CH2, ..., CHn to synthesis filter banks SFB1, SFB2, ..., SFBn. The supplied signals are decoded by ~~means of~~ these synthesis filter banks, and audio signals are obtained over the total frequency domain covered by the sub-band domains. These broadband audio signals are joined together, via main-related filters ISF1, ISF2, ..., ISFn, and ISF1', ISF2', ..., ISFn', by ~~means of~~ combination circuits C and conducted to the sound reproduction means of the reproduction channels present, i.e., in the embodiment shown, to two stereo reproduction channels L and R.

[0014] In the embodiment of the invention as shown in Fig. 2, the coded signals, originating from the storage medium or obtained through transmission, are supplied to sub-band combination circuits SBS1, SBS2, ..., SBSn through the channels CH1, CH2, ..., CHn. The output signals of these sub-band combination circuits are supplied, through respective equalization filters H1, H2, ..., Hn, to the synthesis filter SFB, and from there to the sound reproduction

means of a reproduction channel~~present~~. Although this is not shown in Fig. 2, said output signals may also be supplied to a further synthesis filter through equalization filters, and from there to the sound reproduction means of a further reproduction channel.

5    [0015]    In the embodiment of the invention as shown in Fig. 3, the coded signals, originating from the storage medium or obtained through transmission, are combined in accordance with frequency sub-bands through filters ISF11, ISF12, ..., ISF1k; ISF21, ISF22, ..., ISF2k; ...; ISFn1, ISFn2, ..., ISFnk present in all sub-  
10 channels of the individual input channels, i.e., in accordance with ISF11, ISF21, ..., ISFn1; ISF12, ISF22, ..., ISFn2; ...; ISF1k, ISF2k, ..., ISFnk, by means of respective sub-band combination circuits SBS1, SBS2, ..., SBSn, and supplied to a synthesis filter bank SFB. The supplied channels are coded by means of this  
15 synthesis filter bank and audio signals are obtained, again covering the total frequency domain corresponding to the sub-band domains. These audio signals are subsequently conducted to the sound reproduction means of a corresponding reproduction channel (L). A stereo sound reproduction can be obtained in that the input  
20 signals of the audio signal processing device are also supplied to a second circuit identical to the one depicted in Fig. 3, and in that subsequently, the audio signals obtained by means of this circuit are supplied to the sound reproduction means of a second reproduction channel R. If a sufficiently fine subdivision into  
25 frequency domains is achieved in this embodiment of the invention,

the filters ISF can be given a comparatively simple construction. It was found that the provision of no more than scale factors is sufficient.

[0016] In the embodiment shown in Fig. 4, the coded signals, originating from the storage medium or obtained through transmission, are supplied through 2.1 channels, i.e., through 2 channels covering the entire bandwidth and a so-called "low frequency enhancement (LFE) channel". The signals supplied through the two channels covering the full bandwidth are conducted through "incredible sound filters" ISF11, ISF12, ..., ISF1n, and ISF21, ISF22, ..., ISF2n to the respective sub-band combination circuits SBS1, SBS2, ..., SBSn, whereas the signals supplied through the LFE channel are only supplied to the sub-band combination circuits SBS1 and SBS2 which cover the lowest frequency sub-band domains. The output signals of the sub-band combination circuits are again supplied to a synthesis filter SFB ~~again~~. The output signals of this synthesis filter are subsequently passed on to the sound reproduction means of a corresponding reproduction channel (L). It is true, again, that a stereo sound reproduction can be obtained in that the input signals of the audio signal processing device are also supplied to a second circuit identical to the one depicted in Fig. 4, and in that subsequently, the audio signals obtained by means of this circuit are supplied to the sound reproduction means of a second reproduction channel R. If a usual 5.1 channel arrangement is necessary in this case, three more channels are to

be added in this embodiment in a manner as shown in Fig. 3. Five virtual sound reproduction sources may then be created by means of two sound reproduction channels.

[0017] It will be obvious from the above that any number of  
5 input channels required may be combined with any number of sound reproduction channels, which may or may not be virtual. Neither are the filter means limited to the "incredible sound filters" and equalization filters mentioned here; it is alternatively possible to construct the filter means as a volume control, especially in a  
10 configuration as shown in Fig. 2. The filter means, moreover, may be chosen to be fixed ones or adjustable ones.



ABSTRACT- OF THE DISCLOSURE

An audio signal processing device ~~comprises~~ includes a  
signal supply ~~means to supply~~ for supplying coded audio signal over  
5 more than one input channel and, per input channel, over separate  
frequency sub\_bands domain sub\_channels ~~coded audio signals~~.

————Further filters are used to decode and synthesize the  
audio signals over the total frequency domain.

————Sub\_band combination circuits are used for supplying  
10 respective input channels to the same sub\_band combination circuit  
the signals from the same sub\_band frequency domain audio signals.

Fig. 1